


**TYPE 6870
TRUSTWORTHY
MINIATURE
R.F. AND VIDEO PENTODE**



The BRIMAR 6870 is a trustworthy high slope pentode for use as a small transmitting valve or as a video valve giving a larger output with low anode loads than an ordinary R.F. amplifying pentode.

RATINGS

Heater Voltage	6.3	$\{$	12.6	volts
Heater Current	0.6	$\}$	0.3	amp.
Anode Voltage	300	volts max.
Anode Voltage ($I_a = 0$)	500	volts max.
Anode Dissipation	6.3	watts max.
Screen Voltage	250	volts max.
Screen Voltage ($Ig_2 = 0$)	500	volts max.
Screen Dissipation	2.0	watts max.
Control Grid Current (D.C.)	3.0	mA max.
Control Grid Circuit Resistance—Fixed Bias	0.1	$M\Omega$ max.
Auto Bias	0.5	$M\Omega$ max.
Cathode Current	50	mA max.
Frequency of Operation	150	Mc/s max.
Shock (Intermittent Service)	500	g
Vibration (Continuous Service)	2.5	g

OPERATING CHARACTERISTICS (Class A)

$V_a = Vg_2 = 180$ V, $Vg_1 = Vg_3 = 0$ V, $R_k = 56$ ohm, $C_k = 1,000 \mu F$,
 $V_h = 6.3$ V (parallel connection)

		Min.	Bogey	Max.	
Anode Current	19	25	31	mA
Screen Current	1.5	3.5	5.5	mA
Mutual Conductance	...	7.2	9.0	10.8	mA/V
Anode Impedance	170	...	$k\Omega$
Inner Amplification Factor ($\mu g_1 - g_2$)	28	35	42	...	
Control Grid Voltage for $I_a = 100 \mu A$...	-9	-12	...	volts

INTER-ELECTRODE CAPACITANCES*

Input	8.5	pF
Output	7.0	pF
Control Grid to Anode (max.)	0.025	pF

* With no external shield.

Type 6870 is a commercial equivalent to CV5121.

