

TETRODE

The EIMAC Y834 is a ceramic/metal, forced-air cooled,

The EIMAC Y834 is a ceramic/metal, forced—air cooled, radial—beam tetrode with a rated maximum plate dissipation of 4.5 kW. It is especially designed for UHF LPTV, TV translator and linear amplifier operation requiring low intermodulation distortion up to 1000 MHz. IMD level is better than -52dB.



GENERAL CHARACTERISTICS

ELECTRICAL

Type of Cathode	en
Heating Direct	
Filament Voltage 1	-L te
Filament Current, approximately	
Peak Cathode Current	•
Interelectrode Capacitances, approximately:	ps
Input (g2 tied to g1)	ο Γ
(Natruet (a) find to all	
Cathodo/Anodo	
Amplification Factor $(a1 - a2)$ average))F
Amplification Factor (g1 - g2 average)	7
Transconductance, average	วร

MECHANICAL

Mounting Position Vertic	al
Anode Cooling Forced A	ir
Minimum Airflar ²	
Corresponding Pressure Drop	.Im
Corresponding Pressure Drop	
Maximum Inlet Air Temperature	,°C
Maximum Outlet Air Temperature	^{,0} C
Maximum Temperature 3) ⁰ C
Net Weight	Ko.
Dimensions	ι⁄R
See Drawi	ng

¹In the high frequency operation the cathode is subjected to considerable back bombardment which raises its temperature. After the circuit has been adjusted for proper tube operation, the filament voltage must be reduced to prevent overheating of the cathode with resulting short life.

20April84; Revised April 86

 $^{^2\}mbox{For }30\,^0\mbox{C}$ inlet air temperature and 2 kW anode dissipation.

³At any point on the ceramic insulators. For maximum tube life, this temperature must not exceed 200 °C. The cooling air flow must be established before application of any voltage and maintained for at least one minute after filament voltage has been removed.

OPERATING CONDITIONS

MAXIMUM RATINGS (all potentials refer to cathode)

DC Anode Voltage																												5 kV
DC Grid g2 Voltage .																					•							650 V
DC Grid g1 Voltage .																												
Peak Cathode Current	•		•	•	•	•	•		•		•			•	•					•	•	•	•				•	6 A
DC Anode Current					•		•	•	•	•	•	•	•		•		•		•	•	•	•	•		•	•	•	2 A
Anode Dissipation .	•	•		•	•	•	•	•	•				•	•		•	•				•	•		٠	•	٠		4.5 kW
Grid g2 Dissipation	•		•	•	•	•	•	•	•	•	•			•	•	•		•	•	•	•	•	•	•	•			25 W
Grid g1 Dissipation	•	•	•	•		•	•	•		•	•		•		•	•	•	•	•		•	•	•	•	•	•	•	5 W
Frequency			•			•			•			•			•			•				•						1000 MHz

CLASS A — LINEAR AMPLIFIER FOR TELEVISION TRANSLATOR

Aural and Video Signals Simultaneously

TYPICAL OPERATION

Operating Frequency	474-850 MHz
Bandwidth	10 MHz
Filament Voltage	6 V
DC Anode Voltage	4 kV
DC Grid g2 Voltage	400 V
DC Anode Current (no signal)	0.4 A
Peak Video Power	1.1 kW
Anode Current (black level + audio)	0.8 A
Gain	15.0dB
Intermodulation Products	-54 dB (*)
Distance Between Audio and Video Carriers	4.5 MHz

^(*) Under video level (3-tone test) typical; depending on the cavity/circuit used and adjustments made.

ABSOLUTE MAXIMUM RATINGS: Values shown for each type of service are based on the "absolute system" and are not to be exceeded under any service conditions. These ratings are limiting values outside which the serviceability of the tube may be impaired. In order not to exceed absolute ratings, the equipment designer has the responsibility of determining an average design value for each rating below the absolute value of that rating by a safety factor so that the absolute values will never be exceeded under any usual conditions of supply voltage variation in the equipment itself. It does not necessarily follow that combinations of absolute maximum ratings can be attained simultaneously.

HIGH VOLTAGE: Normal operating voltages used with this tube are deadly. Equipment must be designed properly and operating precautions must be followed. Design all equipment so that no one can come in contact with high voltages. All equipment must include safety enclosures for high-voltage circuits and terminals, with interlock switches to open primary circuits of the power supply and to discharge high-voltage capacitors whenever access doors are opened. Interlock switches must not be bypassed or "cheated" to allow operation with access doors open. Always remember that HIGH VOLTAGE CAN KILL.

INTERELECTRODE CAPACITANCE: The actual internal interelectrode capacitance of a tube is influenced by many variables in most applications such as stray capacitance to the chassis, capacitance added by the socket used, stray capacitance between the tube terminals, and wiring effects. To control the actual capacitance values within the tube as the key component involved, the industry and military services use a standard test procedure as described in Electronic Industries Association Standard RS-191. This requires the use of specially constructed test fixtures which effectively shield all external tube leads from each other and eliminate any capacitance reading to "ground." The test is performed on a cold tube. Other factors being equal, controlling internal tube capacitance in this way normally assures good interchangeability of tubes over a period of time, even if the tube is made by different manufacturers. The capacitance values shown in the manufacturer's technical data, or test specifications, normally are taken in accordance with Standard RS-191.

The equipment designer is, therefore, cautioned to make allowance for the actual capacitance values which will exist in any normal application. Measurements should be taken with the socket and mounting which represent approximate final layout if capacitance values are highly significant in the design.

GRID OPERATION: Maximum control grid dissipation is 5 watts, determined approximately by the product of the dc grid current and the peak positive grid voltage.

SCREEN CRID OPERATION: Maximum screen grid dissipation is 25 watts. With no ac applied to the screen grid, dissipation is simply the product of dc screen voltage and the dc screen current. With screen modulation, dissipation is dependent on rms screen voltage and rms screen current. Plate voltage, plate loading, or bias voltage must never be removed while filament and screen voltages are present, since screen dissipation ratings will be exceeded. A protective spark-gap device should be connected between the screen grid and the cathode to guard against excessive voltage.

