

Specification MAP/CV. 395/Issue 3 Dated 1.3.50 To be read in conjunction with K.1001. excluding clauses 5.2, 5.8.	<u>SECURITY</u>	
	<u>Specification</u> RESTRICTED	<u>Valve</u> UNCLASSIFIED

→ Indicates a change

<u>TYPE OF VALVE</u> - Voltage Stabiliser. <u>CATHODE</u> - Cold. <u>ENVELOPE</u> - Glass, unmetallised. <u>PROTOTYPE</u> - VX. 372.				<u>MARKING</u> See K.1001/4.		
				<u>BASE</u> B8G. See K.1001/AIV/D12.		
<u>RATINGS</u>				<u>CONNECTIONS</u>		
			Note	Pin	Electrode	
Max. Anode take-over voltage	(V)	170	A	1)	Anode	
Max. Anode current	(mA)	45		2)		
Min. Anode current	(mA)	5		3)		
Mean voltage drop across valve operating at 25mA.	(V)	150	A	4)	Cathode	
Max. priming anode current	(mA)	1.0	B	5)		
				6)		
				7)		
				8)		
				<u>DIMENSIONS</u>		
				See K1001/A1/D7		
				<u>Dimension</u>	<u>Min</u>	<u>Max.</u>
				B (mm)	-	29
				F (mm)	70	80
<u>NOTES</u>						
A. These conditions apply with the priming electrode connected to 200V. + ve through 100 kΩ.						
B. If not required for use, the priming electrode shall be joined to the main anode through a resistance of 80,000 Ω						

CV395

TESTS

To be performed in addition to those applicable in K.1001.

Test Conditions				Test	Limits		No. Tested
					Min.	Max.	
a	Priming anode voltage 200 V. through 0.1 M Ω	Main Anode Voltage 0	Main anode current (mA) -	The valve must conduct			100%
b	200 V. through 0.1 M Ω	Increased until current flows.	-	Anode take-over voltage (V)	-	170	100%
c	200 V. through 0.1 M Ω	Adjust	25	Voltage drop between main anode and cathode (V)	145	155	100%
d	200 V. through 0.1 M Ω	Adjust	Changed from 5 to 45.	Regulation (V)	-	5	100%
e	200 V. through 0.1 M Ω	Adjust	Changed from 5 to 25.	Regulation (V)	-	2	100%
f	<p>The valve is to be tested for freedom from noise during operation. For this purpose a calibrated amplifier detector having a response within \pm 2db. of its response at 400 c.p.s. over the range of 50-5000 c.p.s. is to be connected between the anode and cathode. The cathode current is to be varied slowly from 45 mA. to 5 mA. and at no point in this range must the R.M.S. noise input voltage to the amplifier exceed 10mV.</p>						100%