

MINISTRY OF SUPPLY - D. L. R. D. (A)/R. A. E.

Specification MOSA/CV338 Issue 5 Dated 17.11.53 To be read in conjunction with K.1001	<u>SECURITY</u>	
	<u>Specification</u> UNCLASSIFIED	<u>Valve</u> UNCLASSIFIED

→ Indicates a change

TYPE OF VALVE - Full wave gas filled rectifier		<u>MARKING</u> See K.1001/4		
ENVELOPE - Glass, unmetallised		<u>BASE</u> B9G		
CATHODE - Indirectly heated		<u>CONNECTIONS</u>		
PROTOTYPE - VX 3001		Pin	Electrode	
<u>RATING</u> Heater Voltage (V) 5 Heater Current (A) 2.3 Max. R.M.S. Input Voltage (V) 500 Max. Working P.I.V. (kV) 1.3 Max. No Load P.I.V. (kV) 1.4 Max. D.C. Output Current (mA) 250 Max. Peak Anode Current (mA) 850 Max. Reservoir Capacitor (μF) 16 Max. Limiting Impedance (Ω) 150 (Ratings apply to condenser input filter and 50 c/s supply)		Note		
			1	Heater
			2	Anode
			3	Shield
			4	Shield
			5	Heater and Cathode
			6	Shield
			7	Shield
			8	Anode
			9	Heater and Cathode
		<u>DIMENSIONS</u> See K.1001/A1/D2 except		
		Dimension	Min. Max.	
		E (mm)	53.5 60	

NOTES

- A. The sole plate and skirt of the valve must be connected either to cathode or to earth. The ratings are unaffected by the alternative connections.
- B. Heater Voltage must be applied at least 45 seconds before the anode voltage, and 2 minutes before commencing tests.

CV338

TESTS

To be performed in addition to those applicable in K1001

Test Conditions			Test	Limits		No. Tested	Note	
				Min.	Max.			
a	Vh 5.0 AC or DC	Va 0	Ia 0	Ih (A)	2.1	2.5	100% or S	
b	5.0 AC or DC	Vary	-	Striking Vol- tage (V)	-	12	100%	1,2, 3,4.
c	5.0 AC or DC	-	220 mA (per anode)	Arc Drop (V)	-	8	100%	1,2, 4,5.
d	5.0 A.C.	Input voltage 500-0-500 R.M.S. Frequency 50cps. D.C. Load current 250mA. Reservoir Condenser 8μF. Effective impedance in series with each anode 150 Ω		Load Test Output Vol- tage (V)	540	-	100%	1

NOTES

1. Heater voltage must be applied at least 45 seconds before the anode voltage, and 2 mins. before commencing tests.
2. Test to be applied to each anode.
3. Anode voltage must be increased slowly from zero.
4. A series resistance of 250Ω shall be used to limit the current.
5. Anode Current to be read on M2; Input per anode 250V to be read on M3; Arc Drop to be read on M1. (see circuit below)

