## Cathode-Ray Tube Type 14AUP4

The 14AUP4 is a 14° 90° rectangular, electrostatic focus and magnetic deflection direct-view picture tube specifically intended for cathode drive television applications. It has a maximum spot cut-off of 50 volts and a minimum cathode current of 1000 microamperes when operated in cathode drive at a Grid No.2 voltage of 50 volts. Other features of this tube are a short overall length, spherical gray filter glass faceplate, metal-backed screen, a construction which does not require an external ion trap magnet, and a high capacity external conductive coating, which when grounded serves as a filter capacitor and aids in the suppression of radiation. This tube is intended for series string operation and has a heater current of 450 milliamperes.

GENERAL DATA	
Focusing Method	Electrostatic
Deflection Method	Magnetic
Deflection Angles (approx.)	
Horizontal	85 Degrees
Diagonal	90 Degrees
Phosphor	Aluminized P4
Fluorescence	White
Persistence	Medium
Faceplate	Gray Filter Glass
Light Transmission (approx.)	79%
ELECTRICAL DATA	
Heater Voltage	6.3 Volts
Heater Current	0.450 £ 5% Amperes
Heater Warm-up Time <sup>1</sup>	11 Seconds
Direct Interelectrode Capacitances (approx.)	
Cathode to All Other Electrodes	5 uuf
Grid No.1 to All Other Electrodes	6 uuf
External Conductive Coating to Anode2	1500 uuf Max.
	1000 uuf Min.
	•
MECHANICAL DATA	
Overall Length	13 $3/16 \neq 5/16$ Inches
Greatest Bulb Dimensions	
Diagonal	$14 \neq 1/8$ Inches
Width	14 / 1/8 Inches 13 1/16 / 1/8 Inches 10 9/16 / 1/8 Inches
Height	10 9/16 7 1/8 Inches
Neck Length	$51/2 \neq 3/16$ Inches
Minimum Useful Screen Dimensions (Maximum Assured)	9 1/2 x 12 1/16 Inches
Minimum Useful Screen Area	104 Sq.Inches
Bulb Contact - Recessed Small Cavity Cap	J1-21
Base - Small Shell Duodecal 6-pin	B6-63
Basing	12L
Bulb Contact Alignment - J1-21 Contact Aligns wit	
Pin Position No.6 £ 30 D	egrees
MAXIMUM RATINGS (Absolute Maximum Values)	- <b>4</b>
Final Anode Voltage	16,500 Volts dc
Grid No.4 Voltage (Focusing Electrode)4	-500 to 1,100 Volts do
Grid No.2 to Grid No.1 Voltage	70 Volts do

The Rauland Corporation, Chicago, Illinois

GENERAL DATA

(December 26,1957) Page 1 of 3

## Cathode-Ray Tube Type 14AUP4

MAXIMUM RATINGS (Absolute Maximum Values)		
Cathode to Grid No.1 Voltage		
Positive Bias Value	150	Volts
Negative Peak Value	0	Volts
Peak Heater-Cathode Voltage		
During Warm-up Period Not to Exceed 15 Seconds	450	Volts
After Equipment Warm-up Period	200	Volts
Heater Positive with Respect to Cathode	200	Volts
TYPICAL OPERATING CONDITIONS		
Anode Voltage	12,000	Volts dc
Grid No.4 to Grid No.1 Voltage for Focus	•	

Cathode to Grid No.1 Voltage for cut-off<sup>5</sup>

CIRCUIT VALUES
Grid No.1 Circuit Resistance

Grid No.2 to Grid No.1 Voltage

1.5 Max.Megohms

50 Volts dc

0 to ≠ 350 Volts dc


30 to 50 Volts dc

## NOTES

- 1. Heater warm-up time is the time required for the voltage across the heater terminals to increase to 5.0 volts in the JETEC test circuit, with E = 25 volts and series R = 42 ohms.
- 2. External conductive coating must be grounded.

at 100 va Cathode Current

- 3. Grid No.3, Grid No.5 and the Collector are connected internally and are referred to herein as "Final Anode".
- 4. The focus electrode may be modulated to improve overall focus.
- 5. For visual extinction of focused raster. Extinction of stationary focused spot will require that these values be increased approximately 5 volts. The cut-off voltage will change by approximately 2% with 1 KV change of anode voltage.



1. REFERENCE LINE AS DETERMINED BY PLANE C-C of REFERENCE LINE GAUGE RETMA #116.

2. PIN POSITION No. 6 TO BE ALIGNED WITH ANODE BUTTON 230.0

3. DIAGONAL DEFLECTION ANGLE IS 90.0

THE RAULAND CORP.
CHICAGO 47,
ILL.