


T.	Image	Image	$U_f$	$I_f$	$U_{tr}$	$U_o$	$U_p$	$I_o$	$I_p$	$U_{f/k}$	$R_{tr}$	$C_F$
			V	A	V	V	V	mA	mA	V	$\Omega$	$\mu F$
U 107	MOG	8	40	0,1	250	240	700	90	540	350	75	16
U 145	Marc	1	40	0,1								
U 403	Maz	2	40	0,2	200	175		120			50	16
U 4020	Maz	3	40	0,2								
U 404	Maz	1	40	0,1	220	248	750	90	700	470	100	16
UY 4	eur	4	35	0,1								
UY 85	eur	5	38	0,1	110	112		110			0	100
					127	135		110		0	100	
					220	215		110		90	100	
					250	245	700	110	660	550	100	100
1 D 5	Bri	3	40	0,2	250		700	100	450	350	50	16
35 A 3	amer	6	35	0,15	220		700	100				
35 C 3	amer	6	35	0,15	110		330	100				
35 Y 31	Tes	6	35	0,15	120	103	700	140	850	550	125	32
					220	165		140				32
40 SUA	Cos	3	40	0,2	250			75				
40 Z 5 <sup>1)</sup>	amer	7	40	0,15	220		700	90	600	350		

<sup>1)</sup> vide 35 Z 5 - G gr. 14



Equivalents

- U 118 GEC = U 145
- U 119 GEC = UY 85
- U 381 Maz = UY 85
- 38 A 3 amer = UY 85

