





T.			$U_f$	$I_f$	$U_a$	$U_g$	$I_a$	$S$	$\mu$	$R_i$	$P_a$
			V	A	V	V	mA	mA/V	V/V	k $\Omega$	W
6 P 5-G	amer	1	6,3	0,3	$\left\{ \begin{array}{l} 100 \\ 250 \\ 250 \end{array} \right.$	$\left\{ \begin{array}{l} - 5 \\ -13,5 \end{array} \right.$	$\left\{ \begin{array}{l} 2,5 \\ 5 \end{array} \right.$ maximum	$\left\{ \begin{array}{l} 1,15 \\ 1,45 \end{array} \right.$	$\left\{ \begin{array}{l} 13,8 \\ 13,8 \end{array} \right.$	$\left\{ \begin{array}{l} 12 \\ 9,5 \end{array} \right.$	1,25
12 E 5-GT	amer	1	12,6	0,15							
24/76	Maz	1	24	0,08							
56	amer	2	2,5	1							
56-A	amer	2	6,3	0,3							
37	int	2	6,3	0,3	$\left\{ \begin{array}{l} 90 \\ 250 \end{array} \right.$	$\left\{ \begin{array}{l} - 6 \\ -18 \end{array} \right.$	$\left\{ \begin{array}{l} 2,5 \\ 7,5 \end{array} \right.$	$\left\{ \begin{array}{l} 0,8 \\ 1,1 \end{array} \right.$	$\left\{ \begin{array}{l} 9,2 \\ 9,2 \end{array} \right.$	$\left\{ \begin{array}{l} 11,5 \\ 8,4 \end{array} \right.$	

Equivalents

A 256	Vis = 56	37-A	amer = 37	176	amer = 56-A
A 676	Vis = 56-A	56-AS	amer = 56-A	237	amer = 37
G 56	amer = 56	56-S	amer = 56	247-M	amer = 56
G 76	amer = 56-A	67	amer = 37	256	amer = 56
T 56	amer = 56	67-A	amer = 37	276	amer = 56-A
T 76	amer = 56-A	76	amer = 56-A	337	amer = 37
6 P 5-GT	amer = 6 P 5-G	86-M	amer = 56-A	356	amer = 56
27 H	amer = 56	137-A	amer = 37	376	amer = 56-A
27 M	amer = 56	156	amer = 56	4611	amer = 37



T.	$C_{g/a}$	$C_{g/k}$	$C_{a/k}$
	pF	pF	pF
6 P 5-G	2,6	3,4	5,5
37	2,0	3,5	2,9
76	2,8	3,5	2,5

