



T.			U_z	U_{stab}	U_{reg}	$I_{min} \div max$
			V	V	V	mA
GR 27-5	DGL	5		80		0,1 ÷ 6
GR 80/DF	DGL	5	110	80		0,1 ÷ 1
G 2 S 21	STCS	—	135	80		2 ÷ 10
M 8190¹⁾	Mul	6	125	84 ÷ 88	3	0,5 ÷ 3,5
QS 83/3	Marc	1	125	83	1,5	1 ÷ 8
ST 85/10	Tes	2	125	83 ÷ 87		1 ÷ 10
STV 70/6	eur	3	100	72 ÷ 82	3,5	2,5 ÷ 6
STV 75/5 R	STV	3	100	72 ÷ 82		3,5 ÷ 6
TE 2	Osr	5	115	80		0,5 ÷ 3
TE 5	Osr	3	100	85		6 max
T 2742	amer	5	100	80		3 max
T 2742 e	amer	5	100	73 ÷ 80		1 ÷ 5
1 B 46	amer	3	225	82	3	1 ÷ 2
85 A 1	eur	4	125	83 ÷ 87	2	1 ÷ 8
85 A 2	eur	1	125	83 ÷ 87	4	1 ÷ 10
85 A 3	eur	6	130	84 ÷ 88		1,5 ÷ 2
5651	amer	1	115	82 ÷ 90	3	1,5 ÷ 3,5
5783	amer	6	115	82 ÷ 90	3	1,5 ÷ 3,5
5651-WA¹⁾	amer	1	115	82 ÷ 88	2	1,5 ÷ 3,5

¹⁾ vide *4

Equivalents

AG 5209	AEG = 85 A 2	M 8098¹⁾	Mul = 85 A 2	StR 85/10	RFT = 85 A 2
CK 5651	Ray = 5651	M 8142¹⁾	Mul = 85 A 2	STV 85/10	eur = 85 A 2
CK 5651-WA¹⁾	Ray = 5651-WA	OSW 3801	RFT = STV 70/6	OE 3	amer = 85 A 1
CK 5783	Ray = 5783	QS 1209	EEV = QS 83/3	OG 3	amer = 85 A 2
CK 5783-WA¹⁾	Ray = 5783	QS 1212	EEV = 85 A 2	1 B 47	amer = 1 B 46
CK 5783-WB¹⁾	Ray = 5783	QS 1213	EEV = 85 A 2	5783-WA¹⁾	amer = 5783
GR 80/F	DGL = GR 27-5	StR 70/6	RFT = STV 70/6	5783-WB¹⁾	amer = 5783

